



The FS600 Series delivers maximum performance to your home network

- Links up to 5 or 8 PCs or peripherals to your Ethernet network
- Connects network devices at 10 or 100 Mbps
- Plug-and-play installation delivers ease of use
- Silently runs without a fan

Features

- 5- or 8-port Fast Ethernet switch instantly expands your network
- Link up to 5 or 8 PC or Ethernet devices with a fast, auto-switching Ethernet connection
- Supports Windows[®] and Macintosh[®] platforms at speeds of up to 10 or 100 Mbps over Ethernet cables†
- Every port automatically senses the right speed and full/half duplex mode
- AutoUplink™ technology adjusts for two major types of connection cables
- Embedded plug-and-play technology—simply turn it on and it works
- Sleek, compact design

Key Applications

- Multiple PCs connecting to the Internet
- Multiple applications running simultaneously—downloads, voice, music, VoIP
- Multiplayer gaming over the home network
- Multimedia/video streaming within the home
- Networked or shared storage/large file sharing

Features	5-port Ethernet Switch 10/100 Mbps (FS605)	8-port Ethernet Switch 10/100 Mbps (FS608)	5-port Gigabit Ethernet Switch 10/100/1000 Mbps (GS605)	8-port Gigabit Ethernet Switch 10/100/1000 Mbps (GS608)
Performance	1 Gbps	1.6 Gbps	10 Gbps	16 Gbps
Operating System	Windows MAC [®] OS NetWare [®] Linux [®]			
Physical Dimensions (h x w x d)	28.5x147x96.7 mm 1.12x5.79x3.81 in	28.5x171x113.2 mm 1.12x6.73x4.46 in	28.6x147x95.7 mm 1.1x5.8x3.8 in	31x177x117 mm 1.2x7x4.6 in
Warranty	3 year	3 year	2 year	2 year



System Requirements

- UTP Cat 3 (10 Mbps), Cat 5 (100 Mbps)
- Network card for each PC
- Network software (i.e. Windows®, Mac® OS, Linux®)

Physical Specifications

- Dimensions:
 - FS605: 147 x 96.7 x 28.5 mm (5.79 x 3.81 x 1.12 in)
 - FS608: 171 x 113.2 x 28.5 mm (6.73 x 4.46 x 1.12 in)
- Weight: FS605: 0.192 kg (0.424 lb)
FS608: 0.278 kg (0.614 lb)

Power Consumption:

- Maximum power consumption 7.5W
DC operating voltage 7.5V at 1A input

Network Ports

- 5 auto-speed sensing 10/100 Mbps ports; Auto Uplink™ (MDI-MDIX) for connection to other hubs and switches without special cables

Standards Compliance

- IEEE 802.3i 10BASE-T Ethernet
- IEEE 802.3u 100BASE-TX Fast Ethernet
- IEEE 802.3x Flow Control
- Compatible with Microsoft® Windows®, Mac® OS, NetWare®, Linux®

LED Interfaces

- System power
- Link, speed and activity indicators for each port

Safety Agency Approvals for Power Adapter

- C-Tick, CE mark

Environmental Specifications

- Operating temperature: 0° to 40°C (32° to 104°F)
- Operating relative humidity: 10%-90% non-condensing

Emissions Compliance

- CE mark, commercial FCC Part 15 Class B, VCCI Class B, C-Tick, EN 55022, CISPR 22

Warranty

- NETGEAR 3-year Warranty

Package Contents

- 5- or 8-port 10/100 Mbps Fast Ethernet Switch (FS605v3 or FS608v3)
- AC power adapter
- Vertical stand
- Installation guide
- Warranty/support information card

NETGEAR®

350 E. Plumeria Drive
San Jose, CA 95134-1911 USA
1-888-NETGEAR (638-4327)
E-mail: info@NETGEAR.com
www.NETGEAR.com

© 2008 NETGEAR, Inc. NETGEAR, the NETGEAR Logo, NETGEAR Digital Entertainer Logo, Connect with Innovation, FrontView, IntelliFi, PowerShift, ProSafe, RAIDar, RAIDiator, X-RAID, RangeMax, ReadyNAS and Smart Wizard are trademarks of NETGEAR, Inc. in the United States and/or other countries. Other brand names mentioned herein are for identification purposes only and may be trademarks of their respective holder (s). Information is subject to change without notice. All rights reserved.

*Free basic installation support provided for 90 days from date of purchase. Advanced product features and configurations are not included in free basic installation support; optional premium support available.

D-FS605v3/FS608v3-2