



## LICENSE-FREE WALKIE TALKIES

Handfunkgerät

Transceptor

Talkie Walkie

---

# MT100

### 16\* Preset Channels

Channels are preset with Privacy codes to minimize unwanted interference from others.

\* Only Channels 1 to 8 are available by default. Channels 9 to 16 need to be activated by user before they can be selected.)

### Up to 3 km Range

Compact design with extended range.

### Roger Beep

Confirmation tone indicates to others it's clear to talk.

### Power Saver Circuitry

Unique circuit extends battery life when not transmitting or receiving.

### Call Alert

Provides a recognizable alert for incoming calls.



*Nothing Comes Close to a Cobra®*

[www.cobrapmr.com](http://www.cobrapmr.com)

# MT100

## Features

## Benefits

<b>UHF/FM</b>	Ultra-clear long distance reception.
<b>Up to 3 km Range</b>	Extended range capability provides up to 3 km range. (Range will vary depending on terrain and conditions.)
<b>16* Preset Channels</b>	16* channels have been preset with privacy codes to minimize unwanted interference from others.
<b>121 Privacy Codes</b>	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 1936 privacy combinations are possible when the 16 channels are combined with the 121 privacy codes.
<b>Battery Saver Circuitry</b>	A unique circuit extends the life of the batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.
<b>Scan Feature</b>	Allows the user to scan either channels or privacy codes within a channel to locate conversations in progress.
<b>Call Alert</b>	Provides an easily recognizable alert for incoming calls.
<b>Roger Beep Tone</b>	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk.
<b>Auto Squelch</b>	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
<b>LCD Display</b>	Easy to view display provides the radio's status at a glance.
<b>Keystroke Tone Signal</b>	Confirms key activation.
<b>Belt Clip</b>	Secures your microTALK® radio while on the go.
<b>No Licence or Service Fess</b>	High quality band frequencies with no fees.

\* Only Channels 1 to 8 are available by default. Channels 9 to 16 need to be activated by user before they can be selected. Channels 9 to 16 should only be used in countries where these frequencies are allowed by government authorities.

## Unit Specifications - General

<b>Unit Dimension</b> 131mm x 49mm x 36mm (5.16" x 1.93" x 1.42")		<b>SKU#</b>	MT100
<b>Unit Weight</b>		<b>UPC</b>	810026630880
<b>16 Channels with Default Privacy Code</b>	<b>Channel</b>	<b>Freq.(MHz)</b>	<b>Privacy Code</b>
			<b>Type</b> <b>Number</b>
	1	446.00625	DCS 1
	2	446.01875	DCS 11
	3	446.03125	DCS 22
	4	446.04375	DCS 33
	5	446.05625	DCS 44
	6	446.06875	DCS 55
	7	446.08125	DCS 66
	8	446.09375	DCS 77
	9	446.10625	DCS 1
	10	446.11875	DCS 11
	11	446.13125	DCS 22
	12	446.14375	DCS 33
	13	446.15625	DCS 44
	14	446.16875	DCS 55
	15	446.18125	DCS 66
	16	446.19375	DCS 77
		<b>Gift Box Dimension</b>	142mm x 86mm x 86mm (5.59" x 3.39" x 3.39")
		<b>Gift Box Weight</b>	
		<b>Master Pack Qty</b>	4
		<b>Master Pack Bar Code</b>	10810026630887
		<b>Master Pack Dimension</b>	163mm x 184mm x 358mm (6.42" x 3.31" x 14.10")
		<b>Master Pack Weight</b>	
		<b>Battery Pack</b>	3 AAA alkaline batteries per radio (not included)

## 8 Language Manual Includes:



English



Spanish



Swedish



French



Romanian



Dutch



German



Portuguese

\*Specifications subject to change without notice\*

\*All dimensions (H x W x D)\*

Cobra®, microTALK®, Nothing Comes Close to a Cobra®, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

©2020 Altis Technology (Hong Kong) Ltd



\* Packaging is made from recyclable materials.

**Nothing Comes Close to a Cobra®**

MT100 SP 03/20